

High Power
Electrochemical Workstation
ZIVE SHP1005



-1V~+5V@100Amp Battery application
10uHz to 50kHz EIS capability

*For
High Capacity
Lithium Ion / Lithium Polymer
LiFeO₄
NiMH / NiCd
Batteries
Flow Battery*

Electrochemical Workstation ZIVE SHP1005

The **ZIVE SHP1005** is a high current potentiostat/galvanostat/impedance analyzer with a maximum current of 100A for testing high capacity batteries. This system equips CAMLOCK terminal for high current flow to minimize the contact resistance and separated voltage sensing line. The **ZIVE SHP1005** is not potentiostat + high current booster but all in one high power potentiostat/galvanostat/FRA system to enlarge the bandwidth.

The system is designed under FPGA and DSP control with high speed capability.

DAC Control

: Two sets of high speed 16bit DAC(50MHz) for offset & scanning & one set of 16 bit DAC(1MHz) for auxiliary analog output control

ADC Reading

: Two sets of 16 bit 500kHz ADC for reading voltage/current and 4 channel 16 bit 250kHz ADCs for auxiliary data input such as temperature, auxiliary voltage etc. It provides high frequency EIS, fast pulse techniques and high speed sampling time.

The **ZIVE SHP1005** provides impedance measurements over the frequency range 10uHz to 50kHz with 16 EIS techniques. The system's major target application is high capacity battery but it can be used for fuel cell application and other electrochemical application requiring high current under 5Volts . With various advanced software packages, user can widen **ZIVE SHP1005's** flexibility.

System Features

- Versatile high current Potentiostat/Galvanostat/Impedance Analyzer
- 18 EIS techniques capability including multisine & real time EIS at affordable price
- IR measurement in constant current control is available
- Main applications
 - High capacity batteries, fuel cell, supercapacitor, electroplating, electrolysis, etc.
- User defined alias and unit display for auxiliary signal.
- High speed data sampling time
 - 2usec or 3usec depending on data point number
- 3 measurement/control voltage ranges
- 9 measurement/control current ranges
- Internal 542,000 data point storage and continuing experiment regardless of PC failure.
- Full software packages are included as standard
 - EIS test software package(EIS)
 - Energy software package(BAT)
 - Corrosion test software package(COR)
 - Electrochemical analysis software package(EAS)
- Free software upgrade


Hardware Features

- -1 to +5V@100Amp control range
- High current ranges(100A) for high current application
- Smart LCD display
- Independent operation by DSP with FPGA
- Simultaneous 3 auxiliary voltage measurements
- Temperature measurement as standard
- 1 auxiliary analog output
- 3 digital outputs & 1 digital inputs
- Separated power and sensing line
- Max 50kHz EIS capability

• Front View



• Channel View



Versatility

The **ZIVE SHP1005** comes with additional 3 analog inputs (auxiliary voltage input) and 1 analog output along with 3 digital outputs and 1 digital input, and one temperature input for K type thermocouple. It will help users expand the usage of the instrument.

For example,

1. User can measure the voltage between working and reference electrode and, by using 3 additional analog inputs(auxiliary voltage input), user can also measure the voltage between reference and counter electrode and between working and counter electrode as well.
2. With analog output, the system can control flow rate etc. by $\pm 10V$ full scale.
3. User can control on/off of max. 3 devices or 8 address by DO signal.

Safety and Maintenance

1. Even though the communication failure occurs between PC and **ZIVE SHP1005** the system continues its experiment on channel and saves the data into ZIVE memory up to 542,000 data point set. After the communication is restored, ZIVE will transfer saved data to PC automatically or user can transfer data when he/she wants. This function will be highly efficient for long time experiment.
2. User can define a safety condition setting by inputting his/her own safety levels for voltage, current, temperature etc. If the measurement value exceeds this setting value, the system will automatically stop to protect the system and cell.
3. If the control value of voltage or current is different from measured value, the experiment will stop automatically to protect the cell.
4. Automatic calibration function is available for user calibration.
5. The system is controlled from a PC via USB.
6. There is an emergency button to cell off for emergency.

Application

The **ZIVE SHP1005** electrochemical workstation is the best choice for complete DC and impedance characterization of various high capacity batteries, etc.

Batteries



The system is very well adapted for researches on the cycling behavior of battery. It provides various control modes for battery cycling. It can support EVS (electrochemical voltage spectroscopy)/GITT/PITT test. Fast pulse capability for GSM, CDMA test is included in battery test software package. Pulse profile measurement function to check pulse shape is available. For ripple simulation test, sine wave charging/discharging is available.

Fuel Cells



For characterizing the fuel cells and anodic/cathodic process mechanism at development and research grade. This system can be directly used for PEMFC, DMFC, and DEFC etc. The FRA can control an external electronic load for EIS measurement of fuel cell. I-V curve measurements in a full range of available current (autorange option is active during the I-V scan in order to ensure measurement with continuously high resolution).

Super Capacitors



Fast potentiostat circuit with high speed data acquisition (50usec/point, burst mode). This function is well applicable to super capacitor testing, charging/discharging capability is used for this application.

Electroplating / Electrolysis



This system can be used for electroplating experiments.

Potentiostatic, Galvanostatic, Pulse voltammetry, Pulse Amperometry measurement can be used for this application.



For electrolysis experiments,, Potentiostatic, Galvanostatic measurement can be used for this application.

Main Software

The Smart Manager (SM) is to control **ZIVE SHP1005** model and it provides user defined sequential test by using sequence file, technique menu and batch file. The batch file allows the users to do a serial test by combining sequence files and/or technique files.

The SM software is easy to use and supports various electrochemical experiments including functions of system control, schedule file editor, real time graph, analysis graph, user calibration, and data file treatment etc.




Technique list

Basic Techniques

Basic techniques with standard functions

- 1) Potentiostatic
- 2) Galvanostatic
- 3) Double step potentiostatic
- 4) Double step galvanostatic
- 5) OCP measurement
- 6) Potential sweep
- 7) Current sweep
- 8) Cyclic voltammetry
- 9) Fast potential sweep
- 10) Potentiostatic Ru measurement
- 11) Galvanostatic Ru measurement




The above functions can be used sequentially by step control function.

Sequence editor

User can design his/her experiment procedure by using TASK sequential routine editor.

Control Task Parameters

Control Mode		
constant	GSTAT	constant current control
	Crate	constant Crate control
	PSTAT	constant voltage control
	POWER	constant power control
	LOAD	constant load control
	CC-CV	constant current constant voltage control
	Crate-CV	Crate constant voltage control
	CP-CV	constant power constant voltage control
	CL-CV	constant load constant voltage control
	Id	Id control
	Is	Is control
	OCV	OCV control
Step	GSTAT	current step control
	PSTAT	potential step control
Sweep	GSTAT	current sweep control
	FAST-G	fast current sweep control
	PSTAT	potential sweep control
	FAST-P	fast potential sweep control
	ACV	AC voltammetry
EIS	GSTAT	galvanostatic EIS
	PSTAT	potentiostatic EIS
	OCV	OCV EIS
	PSUEDO	pseudo galvanostatic EIS
	HFR G	galvanostatic HFR
	HFR P	potentiostatic HFR
	MisineG	galvanostatic multisine EIS
	MisineP	potentiostatic multisine EIS
Pulse	RTIG	galvanostatic real time EIS
	RTIP	potentiostatic real time EIS
Pulse	Vpulse	voltage pulse control
	Ipulse	current pulse control
Pulse	GSINE	current sine wave control
	PSINE	potential sine wave control
Rest		
ZRA		
Loop		
Device	D OUT	Digital output control
	A OUT	Analog output control
	TEMP CTRL	Temperature controller control
	MUX	Multiplexer control



Sequence editor

- Constant potential, current, C-rate, power, load, OCP
- Sweep potential, current
- Fast sweep potential, current
- Staircase potential, current
- CC-CV, CP-CV, CL-CV, Crate-CV control
- Id, Is control
- EIS control
- Pulse or sinewave control
- Rest(voltage monitoring only)
- Loop(cycle) control

Cut-off(Vertex) Condition

- Time(step, test, loop, cycle)
- Current, current density
- Voltage
- Capacity
- C-rate
- -dV
- |dV/dt|
- |dI/dt|
- Aux1
- Eoc
- etc.

Condition-1		
Item	OP	DeltaValue
Step Time	>=	30
None		
Step End		
Step Time		
Current		
Current Density		
Voltage		
[Capacity]		
-dV		
dV/dt		
dI/dt		
Temp.(°C)		
AUX1		
AUX2		
AUX3		
Test Time		
Loop Time		
Cycle Time		
Eoc		
[WHr]		
LCC(%)		
LCD(%)		
FCC(%)		
Power(W)		
SumQ(Ah)		
SumE(Vh)		
Loop Next		
DI Ch.		
Crate		


Cutoff condition

Sampling Condition

- time, |dI/dt|, |dV/dt|, |dT/dt|, |dA1/dt|, burst time

Flow View


- User can see the sequence flow at a glance.



Flow view

Batch function

User can design batch file including multiple technique files and/or sequence files. With this batch file, user can experiment several techniques/sequence in series automatically.




Smart Manager Advanced Software Package

For a wide range of application, advanced software packages for specific experimental techniques are available as standard. Each software package's upgrade will be provided at free of charge.


EIS Software Package(EIS)

1. Potentiostatic EIS
2. Galvanostatic EIS
3. Pseudo galvanostatic EIS
4. OCP^(*) EIS
5. Potentiodynamic PEIS
6. Galvanodynamic GEIS
7. Potentiodynamic HFR
8. Galvanodynamic HFR
9. Potentiostatic HFR monitor
10. Galvanostatic HFR monitor
11. Multisine potentiostatic EIS
12. Multisine galvanostatic EIS
13. Intermittent potentiostatic EIS
14. Intermittent galvanostatic EIS
15. Real time potentiostatic EIS
16. Real time galvanostatic EIS



Battery intermittent PEIS 3D Nyquist plot by ZMAN


(*) The system measures open circuit potential before for each frequency change and apply AC sine wave on this potential.




Galvanostatic EIS

Potentiodynamic PEIS


Rs, Cp & Idc vs Vdc plot



Potentiostatic EIS




Intermittent Potentiostatic EIS



CC/CV test


CC/CC test



EVS test raw data

EVS graph format
(dQ/dV vs. V)


Energy Software Package(BAT)




BAT software supports IR measurement. in some techniques

1. Battery test techniques


- CC/CV test for cycle life test of lithium battery
- CC/CC test for cycle life test of NiCd or NiMH battery
- Discharging test
- EVS(Electrochemical voltage spectroscopy)
- Variable scan rate CV
- Potentiostatic IV curve
- Galvanostatic IV curve
- Steadystate CV
- GITT(Galvanostatic intermittent titration technique) test
- PITT(Potentiostatic intermittent titration technique) test



GITT Test



PITT Test




Variable scan rate CV

- Pulse mode is available for GSM & CDMA profile. Pulse shape profile can be measured by user's demand.



Pulse shape profile monitor (micro seconds order)



Current sine wave (charge ripple simulation)

2. Control mode

- Charge: CC, CC-CV, pulse, sine wave
- Discharge: CC, CP, CR, pulse, sine wave

3. Cutoff condition

- time, voltage, current, power, temperature, auxV etc.

Various battery charge/discharge test is available including pulse discharge for GSM and CDMA application.



Control & Real Time Graph

Smart Manager provides virtual control panel for control & data acquisition with real time graph.


User can control and monitor for specific channel in details and he/she can monitor data in VOI(value of interest) window and channel status in one window. Real time graph's X,Y axis format will be changed per technique automatically. It can be defined by user's demand per techniques.

For experiment using sequence file or batch file, user can designate X,Y parameter on three different real time graph. The real time graph's format can be also selected.

The real time graph and VOI will be changed depending on DC test or impedance test automatically. The virtual control panel always displays the graph for recent test result. For impedance measurement, wave monitor will be displayed on real time graph to check wave's quality. This monitor can be switched to Lissajous(I vs. E) plot.



Strip Chart





Strip chart recorder function provides real graph function independently. You can monitor 2 Y axis data such as voltage, current, auxV1,2,3, temperature, power, and capacity etc. in real time.

Graph



Smart Manager's graph function is to simplify the operation. There are 3 kinds of graph per each experiment. You can change X, Y1, Y2, Y3, Y4 axis parameter as you want. Each graph provides shortcut buttons. When you click these buttons, the format of the graph will be changed accordingly.





In DC and Cycle graph, whenever you click or the parameters which are related to current such as current, capacity, energy, power, load, etc., are changed into calculated specific value or density value, respectively.

: value divided by weight

: value divided by active area




1) DC Graph

- For general data display
- 4 shortcut buttons: I vs. V, E vs. V, I vs. time, V vs. Q
- Graph parameters: time, Eref, I, Eoc, Id, Aux1, Aux2, Aux3, temp, LogI, Load, ChQ, DchQ, ChQs, DchQs, Ch P, Dch P, Ch-Wh, Dch-Wh, Sum Wh, Sum Q, Sum |Q|, |Q|, Rp, dQ/dV



2) EIS Graph

- For EIS data display
- 3 shortcut buttons: Nyquist plot, Bode plot, Cs vs. frequency
- Graph parameters: Frequency, Zre, -Zim, Zmag, Zph, Y, Yimg, Y, |Y|, Yph, LogZ, LogY, Rs(R-C), Cs(R-C), Rp(R|C), Cp(R|C), Rs(R-L), Ls(R-L), Q(R-L), time, Vdc, Idc, temp, Aux(1,2,3)




3D Bode Plot by ZMAN
Technique used: Potentiodynamic impedance measurement by using a corrosion cell

3) BAT Graph

- For battery cycle data display
- 3 shortcut buttons: cycle capacity, cycle average, Log(cycle No) vs. depth of discharge plot.
- Graph parameters: cycle number, Ch Q, Dch Q, Sum Q, Coulomb Eff, Ch-Wh, Dch-Wh, Sum Wh, Energy Eff, MinV, MaxV, ChQs, DchQ, ChVavg, DchVavg, Vavg

Data Export to ASCII & Excel File




Selectable between 'Convert data on graph only' and 'Convert selected file(s)'


Data Analysis Software

ZIVE data file can be used for analysis by using external IVMAN™ software for DC analysis, IVMAN DA™ software for battery data analysis, IVMAN PA™ software for photo-voltaic cell data analysis and ZMAN™ software for EIS data analysis without license.


ZMAN™ EIS Data Analysis Software

- Model simulation and fitting
- 2D- and 3D-Bode- and Nyquist plots
- Automatic equivalent circuit model search function
- Project concept to handle multiple EIS data analysis
- Parameter plot from fitted elements value
- Compatible with data format from Zahner, Gamry, Ametek etc. (License code is needed.)
- Various weighting algorithm
- Model library and user model
- KK plot
- Batch fitting for project data
- Impedance parameter simulation
- Interpolate bad data
- Black-Nichols plot
- 3D graph setting option
- Improved model editor
- Application model library for automatic searching
- Parameter simulation of model
- Genetic algorithm option for initial guessing
- Automatic initial guessing
- Trace movie function on fitting
- Free for ZIVE's data format(*.seo, *.wis) analysis (No license code required.)
- Circle fitting
- Data editing available (insert, delete, edit)
- Add/subtract element parameters
- Add/subtract model parameters
- Impedance, Z in polar, admittance, Y in Polar, modulus, M in polar, dielectric constant, E in polar. data display
- Empty cell capacitance calculation
- Find file function
- Data replacement by formula function
- Cursor data display
- Model finding result automatic sorting by Chi square value
- R, C R, L R, Q preview & graphic
- ZHIT function
- Mott-Schottky analysis
- Donor density vs. Vfb graph
- C vs. voltage graph







Rp,Cp vs frequency (R | C)




Empty cell capacitance





Donor density vs. Vfb graph and analysis





KK consistency




Mott-Schottky analysis window



C/R-V graph




Bode & Nyquist overlay & 3D plots




IVMAN DA™ Battery Test Data Analysis Software


- Battery test data analysis
- Electrochemical voltage spectroscopy (dQ/dV vs. V)
- Voltage vs. Capacity analysis (V vs. Q)
- Cycle graph (Q vs. cycle)
- Differential voltage graph (dV/dQ vs. Q)




Measured data




V vs. Q




Cycle graph



dQ/dV vs. V



dV/dQ vs. Q




Export ASCII file




IVMAN™ Main Software

- Ideal for DC corrosion data analysis and electro-analytical data analysis
- Initial guessing function on Tafel analysis
- Polarization resistance fitting
- 3D graph
- Find peak function
- Interpolation, differentiation, integration etc.
- Reporting function




Time graph




Find peak menu




CV graph



3D graph




Edit data menu



Universal graph

IVMAN EX™ Extractor

- Extracting data by cycle number or step
- Exporting ASCII file



Electrochemical Workstation ZIVE SHP1005

- High power Battery Jig /holder


- 4 pin probe type



High current Universal Battery Jig 4PK-UCJH4-4P



Prismatic Cell Holder 4PK-PRCJ1



High Power Pouch Cell Holder (Bi-directional) DDPCJ



HCCBJ65L



HCCBJ100L

Specification

Main System	
PC communication	USB2.0 high speed
Line voltage	100~240VAC, 50/60Hz
Max. output power	500Watt
Size	447.1x600x241mm(WxDxH), 29kg
LED indicator	Run, Comm

System	
Cell cable	1 meter working/counter CAMLOK terminal & Reference, working sense shielded type(standard)
Control DAC	DSP with FPGA 2x16bit DAC(50MHz) for bias & scan 1X16bit DAC(1MHz) for analog output
Data acquisition ADC	2x16bit ADCs(500kHz) for voltage, current 4x16bit ADCs(250kHz) for auxiliary voltage and temperature reading
Calibration	Automatic
Filter selection	4ea(5Hz, 1kHz, 500kHz, 8MHz)
Scan rate	0~10V/sec
Internal data memory	542,000 points
LCD display	DC & EIS mode automatically

Power Amplifier(CE)	
Power	500Watt(5V@100A)
Control voltage	-1V to +5V
Max. current	±100A
Control speed selection	4ea
Bandwidth	200kHz
Slew rate	1V/usec

Potentiostat Mode (voltage control)	
Voltage control	
Control voltage range	-1V to +5V, -500mV to +500mV, -50mV to +50mV
Voltage resolution	16 bit per each range
Voltage accuracy	±0.02% fs (gain x1)
Max. scan range	-1V~+5V vs. ref. E
Current measurement	
Current range	10 ranges 100A~100nA 100nA with gatin
Current resolution	16 bit 3mA, 300uA, 30uA, 3uA, 300nA, 30nA, 3nA, 300pA, 30pA, 3pA
Current accuracy	±0.05%fs(gainx1)>10uAf.s

Galvanostat Mode (current control)	
Current control	
Control current range	max. ±100A ± full scale depending on selected range
Current resolution	16 bit 3mA, 300uA, 30uA, 3uA, 300nA, 30nA, 3nA, 300pA, 30pA, 3pA
Current accuracy	±0.05%fs(gainx1)>10uAf.s
Voltage measurement	
Voltage range	+/-5V, 500mV, 50mV
Voltage resolution	16 bit 150uV, 15uV, 1.5uV
Voltage accuracy	±0.02% fs(gain x1)

Electrometer	
Max. input voltage	±5V
Input impedance	>1×10 ¹³ Ω
Bandwidth	>22MHz
CMRR	>114dB

EIS Measurement for System	
Frequency range	10uHz~50kHz
Frequency accuracy	<0.01%
Frequency resolution	5000/decade
Amplitude	0.5mV~3.5Vrms (Potentiostatic) 0.1~70%pp f.s.(Galvanostatic)
Mode	Static EIS: Potentiostatic, Galvanostatic, Pseudogalvanostatic, OCP Dynamic EIS: Potentiodynamic, Galvanodynamic Fixed frequency impedance: Potentiostatic, Galvanostatic, Potentiodynamic, Galvanodynamic Multisine EIS: Potentiostatic, Galvanostatic Intermittent PEIS/GEIS Real time PEIS/GEIS

Interfaces for System	
Auxiliary port	
Digital output	3(open collector)
Digital input	1(photo coupler)
Auxiliary voltage inputs	3 analog inputs: ±10V For measurement of WE vs. CE CE vs. RE or other signal
Analog output	1 analog output: ±10V For flow rate control etc.
Misc. port	
Peripheral communication	I2C to control external devices
Temp. measurement	1 K-type thermocouple input

Software	
Max. step per experiment	1000
Shutdown safety limits	Voltage, current, temperature, etc.
Max. sampling rate	2usec or 3usec depending on data point number
Min. sampling time	Unlimited
Sampling condition	Time, dv/dt, dl/dt, temperature, etc.

PC Requirement	
Operating system	Windows 7/8/10(32bit/64bit OS)
PC specification	Pentium4, RAM 1GB or higher
Display	1600x900 high color or higher
USB	High speed 2.0

General	
Dummy cell	One external dummy cell included
Thermocouple	K-type, 1.5 meter long(option)
Auxiliary cable	Option
Misc. cable	Option
Impedance analysis S/W	ZMAN™ software
DC data analysis S/W	IVMAN™ software package

The specifications are subject to change without notice.
Windows is a registered trade mark of Microsoft Corporation.


Designed by

ZIVE LAB
www.zivelab.com

WonATech

WonATech Co., Ltd.
7, Neunganmal 1-gil, Seocho-gu,
Seoul, 06801, Korea
Phone: +82-2-578-6516
Fax: +82-2-576-2635
E-mail: sales@wonatech.com
Website: www.wonatech.com

Local Distributor



ISO 9000 & ISO 14000 Qualified